

SINAMICS/ SIMOVERT MASTERDRIVES BRAKING RESISTOR
510-620V DC, 50KW, 8 OHM



Figure similar

Order number	
Phase number / of the input voltage	Wert fehlt!
Type of voltage / of the input voltage	Wert fehlt!
Input voltage	Wert fehlt! ... Wert fehlt!
Consumed active power / rated value	12.5 kW
• maximum	75 kW
Input voltage / of the temperature switch / at AC / maximum	Wert fehlt!
Electrical resistance / of the braking resistor	8 Ω
Width	745 mm
Height	305 mm
Depth	485 mm
Net weight	27 kg

Further information

Information und Download Center

https://www.automation.siemens.com/mcms/infocenter/content/en/Pages/order_form.aspx

Technical documentation

<http://w3.siemens.com/mcms/mc-solutions/en/motion-control/support/technical-documentation/Pages/technical-documentation.aspx>

Industry Mall

<https://eb.automation.siemens.com/mall/en/WW/Catag/Product/6SE7028-0ES87-2DC0/all>

Industry Online Support

<http://support.automation.siemens.com/WW/view/en/6SE7028-0ES87-2DC0/all>